



Instrumentation Amplifier Wiring Diagram R1

Supply voltage range: ± 4 V to ± 8 V



Gain	R _F	R _G	Actual Gain
2	0 Ω (short)	None	2
10	8.06 k Ω	2 k Ω	10
50	12.1 k Ω	499 Ω	50.5
100	9.76 k Ω	200 Ω	99.6
200	10 k Ω	100 Ω	202
500	49.9 k Ω	200 Ω	501
1000	100 k Ω	200 Ω	1002



Gain Programming resistors may be installed via direct-solder, push-in machine terminals, or wrap-around turret terminals.